

# MP 472 Quantum Information and Computation

<http://www.thphys.may.ie/staff/jvala/MP472.htm>

## Outline

Open quantum systems

The density operator

Quantum noise (decoherence)

- Applications of quantum operations
  - Dynamics of open quantum systems
  - Quantum process tomography

Quantum error correction

Fault-tolerant quantum  
computation

# Main approaches to dynamics of open quantum systems

## Master equation approaches (density matrix dynamics)

Liouville-von Neumann equation (generalized Schroedinger equation) with for example

- Lindblad superoperator;
- Redfield superoperator;
- etc.

## Quantum trajectory approaches (stochastic wavefunction dynamics)

Stochastic dynamics whose average (over trajectories) reproduces the system dynamics as given by master equation

- Stratonovich approach (to integration of stochastic equations);
- Ito approach.

## Hamiltonian approaches

Full system-environment dynamics with complete or effective description of the environment

- system-environment Hamiltonian dynamics (works for small environment);
- surrogate Hamiltonian approach (effective bath, works for short time).

# Liouville-von Neumann equation

a generalized Schroedinger equation, a master equation that properly describes non-unitary dynamics of an open quantum system

$$d\rho/dt = -(i/\hbar) [H, \rho] + \mathcal{L}(\rho)$$

unitary or      dissipative term  
coherent term

where  $\mathcal{L}(\rho)$  is a dissipative super-operator (an “operator” that acts on operators), H is the Hamiltonian,  $\rho$  is a density matrix of the system.

Generally,  $\mathcal{L}(\rho)$  can be given in the Lindblad form

$$\mathcal{L}(\rho) = \sum_k \lambda_k [2L_k\rho L_k^\dagger - \{L_k^\dagger L_k, \rho\}]$$

where  $\{x,y\} = xy + yx$  is an anticommutator, and  $L_k$  are the Lindblad operators, generators of dissipative dynamics representing system-environment interaction, and  $\lambda$  is a given rate constant.

# Liouville-von Neumann equation: example

## Gaussian pure dephasing (phase flip error) of a harmonic oscillator

We make the following choice:  $L_k = L = H = H^\dagger = \hbar\omega(a^\dagger a + 1/2)$  (Gaussian process)

$$d\rho/dt = -(i/\hbar) [H, \rho] + \lambda[2H\rho H + \{HH, \rho\}] = -(i/\hbar) [H, \rho] - \lambda [H, [H, \rho]]$$

the evolution operator is given as ( $H = a^\dagger a + 1/2$  is not explicitly time dependent):

$$\rho(t) = \exp\left(\int_0^t \{-(i/\hbar) [H, \rho_0] - \lambda [H, [H, \rho_0]]\} dt\right) = \exp(\{-(i/\hbar) [H, \rho_0] - \lambda [H, [H, \rho_0]]\} t)$$

Gaussian term

In the energy representation, the propagator becomes (for the components of  $\rho$ )

$$\rho_{nm}(t) = \exp[-(i/\hbar) \omega_{mn} t - \lambda \omega_{mn}^2 t] \rho_{nm}(0) \quad \omega_{mn} = \omega (m-n)$$

- diagonal elements of  $\rho$ , i.e. populations  $\rho_{mm}$ , are constant with time;
- phase of off diagonal elements of  $\rho$ , i.e. coherences, oscillate with time due to coherent dynamics; the higher is the energy difference between the levels ( $m-n$ ), the linearly faster are the oscillations;
- moduli of coherences decay with time due to dephasing, the higher is the energy difference between the levels ( $m-n$ ), the quadratically faster is the decay.

## Quantum state tomography of a single qubit

Experimental determining an unknown quantum state (of a single qubit)  $\rho$ :

- using a single copy of  $\rho$  it is impossible to characterize the state (recall measurement of non-orthogonal states)
- with many copies (from repeated preparation procedure), it is possible to estimate  $\rho$  as follows:

Using the set  $I/2^{1/2}, X/2^{1/2}, Y/2^{1/2}, Z/2^{1/2}$  which forms an orthonormal set of matrices (with respect to the Hilbert-Schmidt norm  $(A,B)=\text{tr}(A+B)$ ),  $\rho$  can be expanded as

$$\rho = (1/2^{1/2})[\text{tr}(\rho)I + \text{tr}(X\rho)X + \text{tr}(Y\rho)Y + \text{tr}(Z\rho)Z]$$

where the quantities  $\text{tr}(X\rho)$ ,  $\text{tr}(Y\rho)$ , and  $\text{tr}(Z\rho)$  have interpretation of the average value of observable  $X$ ,  $Y$ , and  $Z$  respectively. To get estimates of these quantities, the measurements of  $X$ ,  $Y$  and  $Z$  need to be performed (with increasing number of measurements  $m$ , the uncertainty of the result is decreasing as  $1/m^{1/2}$  via the central limit theorem, so we need a large number of copies of  $\rho$ ).

The density matrix can then be reconstructed from the measurement results.

# Quantum process tomography

Experimental identification of the dynamics of quantum systems.

In general, for  $d$  dimensional quantum system (i.e.  $\dim(\mathcal{H})=d$ ),

- we choose  $d^2$  pure quantum states  $\{|\psi_k\rangle\}$ , chosen so that the corresponding density matrices  $\{|\psi_k\rangle\langle\psi_k|\}$  form a basis for the space of matrices;
- then we subject the state to the process we wish to characterize;
- after completion of this process, we run quantum state tomography to determine the state  $\mathcal{E}(|\psi_j\rangle\langle\psi_j|)$  output from the process.

A way of determining useful representation of  $\mathcal{E}$ : ( $\chi$  matrix representation):

$$\mathcal{E}(\rho) = \sum_k E_k \rho E_k^\dagger$$

To determine the  $E_k$  from measurable parameters, we can consider using a fixed set of  $E'_k$ , which form a basis for the set of operators on the Hilbert space:

$$E_k = \sum_m e_{km} E'_m$$

where  $e_{km}$  are complex numbers. The quantum operation is then given as

$$\mathcal{E}(\rho) = \sum_m E'_m \rho E'_m{}^\dagger \chi_{mn} \quad \chi_{mn} = \sum_i e_{im} e_{in}^*$$

The  $\chi$  matrix completely describes  $\mathcal{E}(\rho)$  once the set of operators  $E'_k$  has been fixed.

## Quantum process tomography

Let  $\rho_k$  (for  $k=1, \dots, d^2$ ) be fixed linearly independent basis for the space of  $d$ -by- $d$  matrices. A convenient choice of operators is  $|n\rangle\langle m|$ . Experimentally, the output state  $\mathcal{E}(|n\rangle\langle m|)$  may be determined by preparing the input states  $|n\rangle$ ,  $|m\rangle$ ,  $|+\rangle = (|n\rangle + |m\rangle)/2^{1/2}$ , and  $|-\rangle = (|n\rangle + i|m\rangle)/2^{1/2}$  and forming linear combinations

$$\mathcal{E}(|n\rangle\langle m|) = \mathcal{E}(|+\rangle\langle +|) + i\mathcal{E}(|-\rangle\langle -|) - (1+i) \mathcal{E}(|n\rangle\langle n|)/2 - (1+i) \mathcal{E}(|m\rangle\langle m|)/2$$

Thus it is possible to determine  $\mathcal{E}(\rho_k)$  by state tomography, for each  $\rho_k$ .

Furthermore, each  $\mathcal{E}(\rho_k)$  may be expressed as linear combination of the basis states,

$$\mathcal{E}(\rho_k) = \sum_j \lambda_{kj} \rho_j$$

and since  $\mathcal{E}(\rho_k)$  is known from the state tomography,  $\lambda_{kj}$  can be determined through linear algebra. We may write

$$E'_m \rho_k E'_n{}^+ = \sum_j \beta_{kj}^{mn} \rho_j$$

where  $\beta_{kj}^{mn}$  are complex numbers which can be determined using linear algebra given the  $E'_m$  and  $\rho_k$  operators. Combining the last two expressions, we have

$$\sum_j \sum_{mn} \chi_{mn} \beta_{kj}^{mn} \rho_j = \sum_j \lambda_{kj} \rho_j$$

From the linear independence of  $\rho_k$ , it follows that for each  $k$ ,

$$\sum_{mn} \beta_{kj}^{mn} \chi_{mn} = \lambda_{kj}$$

This relation is necessary and sufficient condition for the matrix  $\chi$  to give the correct quantum operation  $\mathcal{E}$ .

## Quantum process tomography

Having determined the matrix  $\chi$ , operator sum representation for  $\mathcal{E}$  is obtained as follows. Let the unitary matrix  $U$  diagonalize  $\chi$

$$\chi_{mn} = \sum_{xy} U_{mx} d_x \delta_{xy} U_{ny}^*$$

from which it can be verified that

$$E_i = (d_i^{1/2}) \sum_j U_{ji} E'_j$$

are operational elements for  $\mathcal{E}$ .

---

---

Summary of the algorithm:

- $\lambda$  is experimentally determined using state tomography;
- $\chi$  is determined from the equation  $\beta\chi = \lambda$
- $\chi$  then provides complete description of  $\mathcal{E}$ , including the set of operational elements  $E_i$ .

## Quantum process tomography of a single qubit

In the case of one qubit, we fix the following set of operators

$$E'_0 = I \quad E'_1 = X \quad E'_2 = -iY \quad E'_3 = Z$$

There are 12 parameters, given by  $\chi$ , which determine an arbitrary single qubit quantum operation  $\mathcal{E}$ . These parameters may be measured by four sets of Experiments, for example:

Suppose the input states  $|0\rangle$ ,  $|1\rangle$ ,  $|+\rangle = 2^{-1/2} (|0\rangle + |1\rangle)$ ,  $|-\rangle = 2^{-1/2} (|0\rangle + i|1\rangle)$  are prepared, and the four matrices

$$\rho'_1 = \mathcal{E}(|0\rangle\langle 0|) \quad \rho'_3 = \mathcal{E}(|+\rangle\langle +|) - i\mathcal{E}(|-\rangle\langle -|) - (1-i)(\rho'_1 + \rho'_4) / 2$$

$$\rho'_2 = \mathcal{E}(|1\rangle\langle 1|) \quad \rho'_4 = \mathcal{E}(|+\rangle\langle +|) + i\mathcal{E}(|-\rangle\langle -|) - (1+i)(\rho'_1 + \rho'_4) / 2$$

are determined by quantum state tomography. These correspond to  $\rho'_j = \mathcal{E}(\rho_j)$  where

$$\rho_1 = \begin{pmatrix} 1 & 0 \\ 0 & 0 \end{pmatrix} \quad \rho_2 = \rho_1 X \quad \rho_3 = X \rho_1 \quad \rho_4 = X \rho_1 X$$

Due to the particular choice of basis, and the Pauli representation of  $E'_i$ , we may

express  $\beta = \Lambda \otimes \Lambda$ , where  $\Lambda = (1/2) \begin{pmatrix} I & X \\ X & -I \end{pmatrix}$  so that  $\chi = \Lambda \begin{pmatrix} \rho'_1 & \rho'_2 \\ \rho'_3 & \rho'_4 \end{pmatrix} \Lambda$ .